


PRODUCT SHEET - POWER SUPPLY FROM MILLETEKNIK

Product image



Name, article number and e-number

Name, article number and email number

Name	Item number	E-number (sv)
EN54 MX Mains failure alarm card	A-AL0024C0001	52 577 15

Designation

The cards provide the option to delay mains interruption alarms for: [EN54 24V 1.5A MX S](#), [EN54 24V 5.5A MX M](#), [EN54 24V 7.5A MX M](#),

Area of use

The card is used to time-delay alarms in the event of a power outage.

Technical description

Alarm delay for mains failure is set on dip-switches on the longer board. Times (approx.) that can be set are: 1 minute, 7.5 minutes, 15 minutes or 30 minutes.

Voltage, current and power

Voltage in: 27.3 V DC, (24 V).

Self-consumption is the power outlet the circuit board has when the system is deployed and in battery operation.

Self-consumption

Circuit Boards	Self-consumption (in battery operation)	Comments
EN54 MX Mains failure alarmkort	6 mA standby	41 mA when activated.

Alarm

Alarm for power failure. Switching relay.

Enclosure

The product lacks an enclosure and is mounted in an existing enclosure.

Dimensions, with and without packaging.

Dimensions, height x width x depth. ^a	Dimensions with packaging.
Card 1: 14 x 31 x 12 mm. Card 2: 20 x 51 x 15 mm.	120 x 215 x 165 mm

^aDimensions of product and packaging may differ, this is because the product may lie differently in the packaging.

Height units, fan and IP class.

HE	Built-in fan	IP class
The product lacks an enclosure		

Weight

Weight.

Name	Net weight	Weight incl. packaging
EN54 MX Mains failure alarm card	0.1 kg	0.2 kg

Installation requirements

The card is intended to be installed in devices from Milleteknik in the MX series.

The accessories fits in

Number of cards that fit in the power supply.

Product	Number of cards that can fit ^a
EN54 1.5A MX S	2 (the product consists of two cards that must be installed for the power failure time delay to work).
EN54 5.5A MX M	2 (the product consists of two cards that must be installed for the power failure time delay to work).
EN54 7.5A MX L	2 (the product consists of two cards that must be installed for the power failure time delay to work).

^aThe number of cards/accessories that can fit is the total number that can fit in the housing. Electronic and mechanical limitations may exist.

Requirements that the product meets

The product meets the following requirements.

EMC:	EMC Directive 2014 / 30EU
Electricity:	Low voltage directive: 2014/35 / EU
CE:	CE directive according to: 765/2008

Environment	REACH Regulation: Directive 1907/2006, WEEE Regulation: Directive 20021961E, RoHS Regulation: Directive 2015/863
-------------	--

**NOTE**

The product is part of electrical systems, is subject to the relevant electrical and safety directives and is not a machine according to the Machinery Directive (2006/42/EC).

**Guarantee**

The product has a two-year warranty for manufacturing defects.

Manufacturing, lifespan, environmental impact and recycling

Manufactured by Milleteknik in Partille, Sweden.

The product is designed for a long service life, which reduces the environmental impact. End-of-life products are handed over to the nearest recycling centre.

About this information

All information is published subject to possible errors. Information is updated without prior notice.

Publication date 2025-05-21